

NI 622x Specifications

Specifications listed below are typical at 25 °C unless otherwise noted. Refer to the *M Series User Manual* for more information about NI 622x devices.

このドキュメントの日本語版については、ni.com/manuals を参照してください。
(For a Japanese language version, go to ni.com/manuals.)

Analog Input

Number of channels

NI 6220/6221	8 differential or 16 single ended
NI 6224/6229	16 differential or 32 single ended
NI 6225	40 differential or 80 single ended

ADC resolution 16 bits

DNL No missing codes
guaranteed

INL Refer to the *AI Absolute
Accuracy Table*

Sampling rate

Maximum	250 kS/s single channel, 250 kS/s multi-channel (aggregate)
Minimum	No minimum
Timing accuracy	50 ppm of sample rate
Timing resolution	50 ns

Input coupling DC

Input range ±10 V, ±5 V,
±1 V, ±0.2 V

Maximum working voltage for analog inputs
(signal + common mode) ±11 V of AI GND

CMRR (DC to 60 Hz) 92 dB

Input impedance

Device on

AI+ to AI GND	>10 GΩ in parallel with 100 pF
AI- to AI GND	>10 GΩ in parallel with 100 pF

Device off

AI+ to AI GND	820 Ω
AI- to AI GND	820 Ω

Input bias current ±100 pA

Crosstalk (at 100 kHz)

Adjacent channels	-75 dB
Non-adjacent channels	-90 dB ¹

Small signal bandwidth (-3 dB) 700 kHz

Input FIFO size 4,095 samples

Scan list memory 4,095 entries

Data transfers

PCI/PXI devices	DMA (scatter-gather), interrupts, programmed I/O
USB devices	USB Signal Stream, programmed I/O

¹ For USB-6225 devices, channel AI <0..15> crosstalk to channel AI <64..79> is -71 dB; applies to channels with 64-channel separation, for example, AI (x) and AI (x + 64).

Overvoltage protection (AI <0..79>, AI SENSE, AI SENSE 2)

Device on±25 V for up to
two AI pins

Device off±15 V for up to
two AI pins

Input current during
overvoltage condition±20 mA max/AI pin

Settling Time for Multichannel Measurements




Accuracy, full scale step, all ranges

±90 ppm of step (±6 LSB)4 μs convert interval

±30 ppm of step (±2 LSB)5 μs convert interval

±15 ppm of step (±1 LSB)7 μs convert interval

Typical Performance Graphs



Analog Output

Number of channels	
NI 6220/6224	0
NI 6221/6225	2
NI 6229	4
DAC resolution	16 bits
DNL	±1 LSB
Monotonicity	16 bit guaranteed
Maximum update rate	
1 channel	833 kS/s
2 channels	740 kS/s per channel
3 channels	666 kS/s per channel
4 channels	625 kS/s per channel
Timing accuracy	50 ppm of sample rate
Timing resolution	50 ns
Output range	±10 V
Output coupling	DC
Output impedance	0.2 Ω
Output current drive	±5 mA
Overdrive protection	±25 V
Overdrive current	10 mA
Power-on state	±20 mV ¹
Power-off glitch	400 mV for 200 ms
Output FIFO size	8,191 samples shared among channels used
Data transfers	
PCI/PXI devices	DMA (scatter-gather), interrupts, programmed I/O
USB devices	USB Signal Stream, programmed I/O

AO waveform modes:

- Non-periodic waveform
- Periodic waveform regeneration mode from onboard FIFO
- Periodic waveform regeneration from host buffer including dynamic update

Settling time, full scale step	
15 ppm (1 LSB)	6 μs
Slew rate	15 V/μs
Glitch energy	
Magnitude	100 mV
Duration	2.6 μs

Calibration (AI and AO)

Recommended warm-up time	15 minutes
Calibration interval	1 year

¹ For all USB-6221/6229 Screw Terminal devices, when powered on, the analog output signal is not defined until after USB configuration is complete.

AI Absolute Accuracy Table

Nominal Range	Positive Full Scale	Negative Full Scale	Residual Gain Error (ppm of Reading)	Gain Tempco (ppm/°C)	Reference Tempco	Residual Offset Error (ppm of Range)	Offset Tempco (ppm of Range/°C)	INL Error (ppm of Range)	Random Noise, σ (μ Vrms)	Absolute Accuracy at Full Scale ¹ (μ V)	Sensitivity ² (μ V)
10	-10		75	25	5	20	57	76	244	3,100	97.6
5	-5		85	25	5	20	60	76	122	1,620	48.8
1	-1		95	25	5	25	79	76	30	360	12.0
0.2	-0.2		135	25	5	80	175	76	13	112	5.2

AbsoluteAccuracy = Reading · (GainError) + Range · (OffsetError) + NoiseUncertainty

GainError = ResidualAGainError + GainTempco · (TempChangeFromLastInternalCal) + ReferenceTempco · (TempChangeFromLastExternalCal)

OffsetError = ResidualAOffsetError + OffsetTempco · (TempChangeFromLastInternalCal) + INL_Error

NoiseUncertainty = $\frac{\text{RandomNoise} \cdot 3}{\sqrt{100}}$ For a coverage factor of 3 σ and averaging 100 points.

¹ Absolute accuracy at full scale on the analog input channels is determined using the following assumptions:

TempChangeFromLastExternalCal = 10 °C

TempChangeFromLastInternalCal = 1 °C

number_of_readings = 100

CoverageFactor = 3 σ

For example, on the 10 V range, the absolute accuracy at full scale is as follows:

GainError = 75 ppm + 25 ppm · 1 + 5 ppm · 10

GainError = 150 ppm

OffsetError = 20 ppm + 57 ppm · 1 + 76 ppm

OffsetError = 153 ppm

NoiseUncertainty = $\frac{244 \mu\text{V} \cdot 3}{\sqrt{100}}$ NoiseUncertainty = 73 μ V

AbsoluteAccuracy = 10 V · (GainError) + 10 V · (OffsetError) + NoiseUncertainty AbsoluteAccuracy = 3,100 μ V

² Sensitivity is the smallest voltage change that can be detected. It is a function of noise.

Accuracies listed are valid for up to one year from the device external calibration.

AO Absolute Accuracy Table

Nominal Range		Residual Gain Error (ppm of Reading)	Gain Tempco (ppm/°C)	Reference Tempco	Residual Offset Error (ppm of Range)	Offset Tempco (ppm of Range/°C)	INL Error (ppm of Range)	Absolute Accuracy at Full Scale ¹ (µV)
Positive Full Scale	Negative Full Scale							
10	-10	90	10	5	40	5	128	3,230

¹ Absolute Accuracy at full scale numbers is valid immediately following internal calibration and assumes the device is operating within 10 °C of the last external calibration. Accuracies listed are valid for up to one year from the device external calibration.

AbsoluteAccuracy = OutputValue · (GainError) + Range · (OffsetError)
GainError = ResidualGainError + GainTempco · (TempChangeFromLastInternalCal) + ReferenceTempco · (TempChangeFromLastExternalCal)
OffsetError = ResidualOffsetError + AOffsetTempco · (TempChangeFromLastInternalCal) + INL_Error

Digital I/O/PFI

Static Characteristics

Number of channels	
NI 6220/6221 (68-pin)/622524 total 8 (P0.<0..7>) 16 (PFI <0..7>/P1, PFI <8..15>/P2)
PCI-6221 (37-pin)10 total 2 (P0.<0, 1>) 8 (PFI <0..7>/P1)
NI 6224/622948 total 32 (P0.<0..31>) 16 (PFI <0..7>/P1, PFI <8..15>/P2)
Ground referenceD GND
Direction controlEach terminal individually programmable as input or output
Pull-down resistor50 k Ω typical, 20 k Ω minimum
Input voltage protection ¹ \pm 20 V on up to two pins

Waveform Characteristics (Port 0 Only)

Terminals used	
NI 6220/6221 (68-pin)/6225Port 0 (P0.<0..7>)
PCI-6221 (37-pin)Port 0 (P0.<0, 1>)
NI 6224/6229Port 0 (P0.<0..31>)
Port/sample size	
NI 6220/6221 (68-pin)/6225Up to 8 bits
PCI-6221 (37-pin)Up to 2 bits
NI 6224/6229Up to 32 bits
Waveform generation (DO) FIFO2,047 samples
Waveform acquisition (DI) FIFO2,047 samples
DO or DI Sample Clock frequency ²0 to 1 MHz

Data transfers	
PCIPXI devicesDMA (scatter-gather), interrupts, programmed I/O
USB devicesUSB Signal Stream, programmed I/O
DO or DI Sample Clock source ³Any PFI, RTSI, AI Sample or Convert Clock, AO Sample Clock, Ctr <i>n</i> Internal Output, and many other signals
PFI/Port 1/Port 2 Functionality⁴	
FunctionalityStatic digital input, static digital output, timing input, timing output
Timing output sourcesMany AI, AO, counter, DI, DO timing signals
Debounce filter settings125 ns, 6.425 μ s, 2.56 ms, disable; high and low transitions; selectable per input

¹ Stresses beyond those listed under *Input voltage protection* may cause permanent damage to the device.

² Performance can be dependent on bus latency and volume of bus activity.

³ The digital subsystem does not have its own dedicated internal timing engine. Therefore, a sample clock must be provided from another subsystem on the device or an external source.

⁴ Port 2 is not available on PCI-6221 (37-pin) devices.

Recommended Operation Conditions

PCI/PXI devices

Level	Min	Max
Input high voltage (V_{IH})	2.2 V	5.25 V
Input low voltage (V_{IL})	0 V	0.8 V
Output high current (I_{OH})		
P0.<0..31>	—	-24 mA
PFI <0..15>/P1/P2	—	-16 mA
Output low current (I_{OL})		
P0.<0..31>	—	24 mA
PFI <0..15>/P1/P2	—	16 mA





USB devices

Level	Min	Max
Input high voltage (V_{IH})	2.2 V	5.25 V
Input low voltage (V_{IL})	0 V	0.8 V
Output high current (I_{OH})		
P0.<0..15>	—	-24 mA
P0.<16..31>	—	-16 mA
PFI <0..15>/P1/P2	—	-16 mA
Output low current (I_{OL})		
P0.<0..15>	—	24 mA
P0.<16..31>	—	16 mA
PFI <0..15>/P1/P2	—	16 mA

Electrical Characteristics

Level	Min	Max
Positive-going threshold (V_{T+})	—	2.2 V
Negative-going threshold (V_{T-})	0.8 V	—
Delta VT hysteresis ($V_{T+} - V_{T-}$)	0.2 V	—
I_{IL} input low current ($V_{in} = 0$ V)	—	-10 μ A
I_{IH} input high current ($V_{in} = 5$ V)	—	250 μ A

Digital I/O Characteristics



General-Purpose Counter/Timers

Number of counter/timers	2
Resolution	32 bits
Counter measurements	Edge counting, pulse, semi-period, period, two-edge separation
Position measurements	X1, X2, X4 quadrature encoding with Channel Z reloading; two-pulse encoding
Output applications	Pulse, pulse train with dynamic updates, frequency division, equivalent time sampling
Internal base clocks	80 MHz, 20 MHz, 0.1 MHz
External base clock frequency	0 MHz to 20 MHz
Base clock accuracy	50 ppm
Inputs	Gate, Source, HW_Arm, Aux, A, B, Z, Up_Down
Routing options for inputs	Any PFI, RTSI, PXI_TRIG, PXI_STAR, analog trigger, many internal signals
FIFO	2 samples
Data transfers	
PCI/PXI devices	Dedicated scatter-gather DMA controller for each counter/timer; interrupts; programmed I/O
USB devices	USB Signal Stream, programmed I/O

Frequency Generator

Number of channels	1
Base clocks	10 MHz, 100 kHz
Divisors	1 to 16
Base clock accuracy	50 ppm
Output can be available on any PFI or RTSI terminal.	

Phase-Locked Loop (PLL)

Number of PLLs	1
Reference signal	PXI_STAR, PXI_CLK10, RTSI <0..7>
Output of PLL	80 MHz Timebase; other signals derived from 80 MHz Timebase including 20 MHz and 100 kHz Timebases

External Digital Triggers

Source	Any PFI, RTSI, PXI_TRIG, PXI_STAR
Polarity	Software-selectable for most signals
Analog input function	Start Trigger, Reference Trigger, Pause Trigger, Sample Clock, Convert Clock, Sample Clock Timebase
Analog output function	Start Trigger, Pause Trigger, Sample Clock, Sample Clock Timebase
Counter/timer functions	Gate, Source, HW_Arm, Aux, A, B, Z, Up_Down,
Digital waveform generation (DO) function	Sample Clock
Digital waveform acquisition (DI) function	Sample Clock

Device-To-Device Trigger Bus

PCI devices.....	RTSI <0..7> ¹
PXI devices.....	PXI_TRIG <0..7>, PXI_STAR
USB devices	None
Output selections	10 MHz Clock; frequency generator output; many internal signals
Debounce filter settings.....	125 ns, 6.425 μs, 2.56 ms, disabled; high and low transitions; selectable per input

Bus Interface

PCI/PXI devices	3.3 V or 5 V signal environment
USB devices	USB 2.0 Hi-Speed or full-speed ²
DMA channels (PCI/PXI devices).....	6, analog input, analog output, digital input, digital output, counter/timer 0, counter/timer 1
USB Signal Stream (USB devices).....	4, can be used for analog input, analog output, digital input, digital output, counter/timer 0, counter/timer 1

All PXI-622x devices support one of the following features:

- May be installed in PXI Express hybrid slots
- Or, may be used to control SCXI in PXI/SCXI combo chassis

Table 1. PXI/SCXI Combo and PXI Express Chassis Compatibility

M Series Device	M Series Part Number	SCXI Control in PXI/SCXI Combo Chassis	PXI Express Hybrid Slot Compatible
PXI-6220	191332B-04	No	Yes
PXI-6221	191332B-03	No	Yes
	191332B-13	Yes	No
PXI-6224	191332B-02	No	Yes
PXI-6225	192227A-01	No	Yes
PXI-6229	191332B-01	No	Yes
	191332B-11	Yes	No
Earlier versions of PXI-6220/6221/6224/6229	191332A-0x	Yes	No

Power Requirements

Current draw from bus during no-load condition³

+5 V.....	0.02 A ⁴
+3.3 V.....	0.25 A ⁴
+12 V.....	0.15 A

Current draw from bus during AI and AO overvoltage condition³

+5 V.....	0.02 A ⁴
+3.3 V.....	0.25 A ⁴
+12 V.....	0.25 A



Caution USB-622x devices must be powered with NI offered AC adapter or a National Electric Code (NEC) Class 2 DC source that meets the power requirements for the device and has appropriate safety certification marks for country of use.

¹ In other sections of this document, *RTSI* refers to *RTSI* <0..7> for PCI devices or *PXI_TRIG* <0..7> for PXI devices.

² If you are using a USB M Series device in full-speed mode, device performance will be lower and you will not be able to achieve maximum sampling/update rates.

³ Does not include P0/PFI/P1/P2 and +5 V terminals.

⁴ PXI-6221 (37-pin) devices do not use +3.3 V from the bus. The 3.3 V current draw, shown in the *Power Requirements* section, comes from the +5 V instead.

USB power supply requirements 11 to 30 VDC, 20 W,
locking or non-locking
power jack with 0.080"
diameter center pin,
5/16–32 thread for
locking collars

Power Limits



Caution Exceeding the power limits may cause unpredictable behavior by the device and/or PC/chassis.

PCI devices

+5 V terminal (connector 0) 1 A max¹
+5 V terminal (connector 1) 1 A max¹

PXI devices

+5 V terminal (connector 0) 1 A max¹
+5 V terminal (connector 1) 1 A max¹
P0/PFI/P1/P2 and +5 V
terminals combined 2 A max

USB devices

+5 V terminal 1 A max¹
P0/PFI/P1/P2 and +5 V
terminals combined 2 A max
Power supply fuse 2 A, 250 V

Physical Requirements

Printed circuit board dimensions

PCI-6220/6221/6224/
6225/6229 9.7 cm × 15.5 cm
(3.8 in. × 6.1 in.)
PXI-6220/6221/6224/
6225/6229 Standard 3U PXI

Enclosure dimensions (includes connectors)

USB-6221/6225/6229
Screw Terminal 26.67 × 17.09 × 4.45 cm
(10.5 × 6.73 × 1.75 in.)
USB-6221/6229 BNC 28.6 × 17 × 6.9 cm
(11.25 × 6.7 × 2.7 in.)
USB-6225 Mass Termination 18.8 × 17.09 × 4.45 cm
(7.4 × 6.73 × 1.75 in.)
USB-6221/6225/6229 OEM Refer to the
*NI USB-622x/625x OEM
User Guide*

Weight

PCI-6220 91 g (3.2 oz)
PCI-6221 (68-pin) 92 g (3.2 oz)
PCI-6221 (37-pin) 95 g (3.3 oz)
PCI-6224 99 g (3.5 oz)
PCI-6225 103 g (3.6 oz)
PCI-6229 101 g (3.5 oz)
PXI-6220 158 g (5.5 oz)
PXI-6221 162 g (5.7 oz)
PXI-6224 170 g (5.9 oz)
PXI-6225 174 g (6.1 oz)
PXI-6229 171 g (6.0 oz)
USB-6221 Screw Terminal 1.2 kg (2 lb 10 oz)
USB-6225/6229
Screw Terminal 1.24 kg (2 lb 11 oz)
USB-6225 Mass Termination 907 g (2 lb)
USB-6221 OEM 131 g (4.6 oz)
USB-6225/6229 OEM 162 g (5.7 oz)

I/O connector

PCI/PXI-6220/6221 (68-pin) 1 68-pin VHDCI
PCI/PXI-6224/6225/6229 2 68-pin VHDCI
PCI-6221 (37-pin) 1 37-pin D-SUB
USB-6221 Screw Terminal 64 screw terminals
USB-6225/6229
Screw Terminal 128 screw terminals
USB-6221 BNC 20 BNCs and
30 screw terminals
USB-6229 BNC 30 BNCs and
60 screw terminals
USB-6225 Mass Termination 2 68-pin SCSI

USB-6221/6225/6229 Screw Terminal/USB-6221/6229 BNC
screw terminal wiring 16–28 AWG

Maximum Working Voltage²

NI 6220/6221/6224/6225/6229
Channel to earth 11 V,
Measurement Category I



Caution Do *not* use for measurements within Categories II, III, or IV.

¹ Has a self-resetting fuse that opens when current exceeds this specification.

² *Maximum working voltage* refers to the signal voltage plus the common-mode voltage.

Environmental

Operating temperature

PCI/PXI devices.....0 to 55 °C

USB devices.....0 to 45 °C

Storage temperature.....-20 to 70 °C

Humidity.....10 to 90% RH,
noncondensing

Maximum altitude2,000 m

Pollution Degree
(indoor use only)2

Shock and Vibration (PXI Devices Only)

Operational shock.....30 g peak, half-sine,
11 ms pulse
(Tested in accordance
with IEC-60068-2-27.
Test profile developed
in accordance with
MIL-PRF-28800F.)

Random vibration

Operating5 to 500 Hz, 0.3 g_{rms}

Nonoperating5 to 500 Hz, 2.4 g_{rms}
(Tested in accordance
with IEC-60068-2-64.
Nonoperating test profile
exceeds the requirements
of MIL-PRF-28800F,
Class 3.)

Safety

This product is designed to meet the requirements of the following standards of safety for electrical equipment for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1



Note For UL and other safety certifications, refer to the product label or visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.

Electromagnetic Compatibility

This product is designed to meet the requirements of the following standards of EMC for electrical equipment for measurement, control, and laboratory use:

- EN 61326 EMC requirements; Minimum Immunity
- EN 55011 Emissions; Group 1, Class A
- CE, C-Tick, ICES, and FCC Part 15 Emissions; Class A



Note For EMC compliance, operate this device with shielded cables.

CE Compliance

This product meets the essential requirements of applicable European Directives, as amended for CE marking, as follows:

- 73/23/EEC; Low-Voltage Directive (safety)
- 89/336/EEC; Electromagnetic Compatibility Directive (EMC)



Note Refer to the Declaration of Conformity (DoC) for this product for any additional regulatory compliance information. To obtain the DoC for this product, visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.

Environmental Management

National Instruments is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial not only to the environment but also to NI customers.

For additional environmental information, refer to the *NI and the Environment* Web page at ni.com/environment. This page contains the environmental regulations and directives with which NI complies, as well as any other environmental information not included in this document.

Waste Electrical and Electronic Equipment (WEEE)



EU Customers At the end of their life cycle, all products *must* be sent to a WEEE recycling center. For more information about WEEE recycling centers and National Instruments WEEE initiatives, visit ni.com/environment/weee.htm.

电子信息产品污染控制管理办法（中国 RoHS）



中国客户 National Instruments 符合中国电子信息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息, 请登录 ni.com/environment/rohs_china。(For information about China RoHS compliance, go to ni.com/environment/rohs_china.)




Figure 1. PCI/PXI-6220 Pinout




Figure 2. PCI/PXI-6221 (68-Pin) Pinout




Figure 3. PCI-6221 (37-Pin) Pinout




Figure 4. USB-6221 Screw Terminal Pinout




Figure 5. USB-6221 BNC Top Panel and Pinout




Figure 6. PCI/PXI-6224 Pinout




Figure 7. PCI/PXI-6225 Pinout




Figure 8. USB-6225 Screw Terminal Pinout




Figure 9. USB-6225 Mass Termination Pinout




Figure 10. PCI/PXI-6229 Pinout




Figure 11. USB-6229 Screw Terminal Pinout




Figure 12. USB-6229 BNC Top Panel and Pinout

National Instruments, NI, ni.com, and LabVIEW are trademarks of National Instruments Corporation. Refer to the *Terms of Use* section on ni.com/legal for more information about National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products, refer to the appropriate location: **Help>Patents** in your software, the `patents.txt` file on your CD, or ni.com/patents.